

RPM Meter

MODEL: 0201-2001



ESLPL® Soft key pad Auto Calibration through keys Auto Least Count Range 2-99 RPM : Least Count 0.01 RPM Range 100-999 RPM : Least Count 0.1 RPM Range 1000-9999 RPM : Least Count 1 RPM Input through single proximity switch



Specifications	Available Options
----------------	-------------------

Specifications	Available Options
----------------	-------------------

Display :	7 Segment LEDs
-----------	----------------

Input :	Proximity Switch
---------	------------------

Calibration :	Through Key
---------------	-------------



Mobile:(+91) 9811482048
Mobile:(+91) 9311482051

Embedded System Laboratories Pvt. Ltd.

86, Gurudwara Road, Jawahar Colony, Near Laxmi Dairy,
N.I.T. Faridabad,-121005, Haryana, India

website : <https://www.eslpl.com>, email : sales@eslpl.com